

(No Model.)

2 Sheets—Sheet 1.

**E. HEADLEY & W. G. HORTON.
REGISTERING TOY BANK.**

No. 450,071.

Patented Apr. 7, 1891.

Fig. 1.




Fig. 2.





Fig. 6.

Witnesses:

J.B.McGinn.
C.M.Buckley



Inventors
Elwood Headley
William G. Norton
by Pennsylvania Power
and Light Company

(No Model.)

2 Sheets—Sheet 2.

E. HEADLEY & W. G. HORTON.
REGISTERING TOY BANK.

No. 450,071.

Patented Apr. 7, 1891.

Fig. 3.




Fig. 4.





Fig. 5.

Witnesses:

J. B. McGivern
W. M. Buckley



Inventors
Edward Headley,
William G. Horton,
by Connally Bros
attp.

UNITED STATES PATENT OFFICE.

ELWOOD HEADLEY AND WILLIAM G. HORTON, OF NEWARK, NEW JERSEY.

REGISTERING TOY BANK.

SPECIFICATION forming part of Letters Patent No. 450,071, dated April 7, 1891.

Application filed November 6, 1890. Serial No. 370,492. (No model.)

To all whom it may concern:

Be it known that we, ELWOOD HEADLEY and WILLIAM G. HORTON, citizens of the United States, residing at Newark, in the county of Essex and State of New Jersey, have invented certain new and useful Improvements in Registering Toy Banks; and we do hereby declare the following to be a full, clear, and exact description of the invention, reference being had to the accompanying drawings, which form part of this specification.

This invention has relation to that class of toy savings-banks or coin-receptacles wherein the coins deposited one by one are registered by means of figured dials, and the opening of the bank or receptacle is dependent upon the depositing of a certain number of coins.

The bank or receptacle embodying our invention is so constructed that when a coin of a certain value or denomination is passed through a slot in the upper portion of the bank it will come into proper relation with the dial-operating mechanism and cause the same to become operative both for the purpose of conveying the coin into its proper compartment and for turning the dial or dials.

The object of our invention is to greatly simplify the coin-controlled mechanism of the bank and to render it more certain and easy of operation.

Our invention consists in the novel construction, combinations, and arrangements of parts hereinafter described.

Referring to the accompanying drawings, Figure 1 is a perspective view of the bank or receptacle closed and ready for use. Fig. 2 is a vertical longitudinal sectional view of the same, taken immediately back of the front wall. Fig. 3 is a perspective view of the coin-controlled mechanism, taken from the inside of the bank. Fig. 4 is an elevation of the coin-controlled mechanism arranged upon the inner surface of the front wall. Fig. 5 is a perspective view of the trap-door closing the opening through which the coins are taken from the bank. Fig. 6 is a perspective view of one of the registering-dials.

A designates the bank-receptacle, which is in the form of an oblong rectangular box or chest made, preferably, of cast iron and of attractive configuration. In the upper part or

top of the bank, near the front wall thereof, is formed a slot *a* of such dimensions as will freely admit of the passage of a coin of a certain diameter and thickness, say one cent. 55 This slot communicates with a vertical passage-way formed by the flanges or offsets *a'*, which are preferably cast with and upon the front wall of the bank. Below these flanges is formed a horizontal shelf *a*², upon which 60 the deposited coin first rests after being passed into the bank. Above this shelf is formed a beveled or rounded guide-piece *a*³, which serves to hold the coin at a proper distance from the wall of the bank to make it effective 65 as a part of the operative mechanism.

B designates a horizontal slide arranged between the shelf *a*² and the flanges *a'* *a'* and located between suitable guides cast on the front wall of the bank. This slide carries on 70 its inner end a plate-spring *b*, through which the dials are operated, and on its outer end, which projects through an opening in one end of the bank, a knob or thumb-piece *b'*, by which the slide is reciprocated. A slot *b*³ is 75 formed in the slide *B* at such a point that when the slide is thrust inwardly to its full extent of movement the deposited coin will just pass through the slot and rest on the ledge below, a small portion of the coin projecting above the slide, as shown in Fig. 3 of the drawings. A lug or lugs *c* *c* are formed on the upper surface of the slide a little way back of the middle of the slot *b*³ and of such height that the upper edge of a coin of the 80 proper value when resting upon the shelf below will be slightly higher than the tops of the lugs.

C designates a plate-spring fastened at one end to the front wall of the bank and having 90 its free extension or limb *C'* bent inwardly and downwardly, so as to rest upon the upper surface of the slide and terminate at the outer extremity of the slot *b*³. When the slide is drawn outward without a coin, or with a coin 95 of less than the proper diameter, the lugs *c* *c* come in contact with the end *C'* of the spring *C* and the movement of the slide is arrested, so that it cannot be drawn out the distance required for conveying a coin into the body 100 of the bank. When, however, a coin of the proper diameter is in the slot *b*³ and the slide

